

Cooperative Lattice Coding and Decoding

Arul Murugan, Kambiz Azarian, and Hesham El Gamal

Abstract

A novel lattice coding framework is proposed for outage-limited cooperative channels. This framework provides practical implementations for the optimal cooperation protocols proposed by Azarian *et al.*. In particular, for the relay channel we implement a variant of the dynamic decode and forward protocol, which uses orthogonal constellations to reduce the channel seen by the destination to a single-input single-output time-selective one, while inheriting the same diversity-multiplexing tradeoff. This simplification allows for building the receiver using traditional belief propagation or tree search architectures. Our framework also generalizes the coding scheme of Yang and Belfiore in the context of amplify and forward cooperation. For the cooperative multiple access channel, a tree coding approach, matched to the optimal linear cooperation protocol of Azarain *et al.*, is developed. For this scenario, the MMSE-DFE Fano decoder is shown to enjoy an excellent tradeoff between performance and complexity. Finally, the utility of the proposed schemes is established via a comprehensive simulation study.

1 Introduction

Lately, cooperative communications has been the focus of intense research activities. As a consequence, we now have a wealth of results covering a wide range of channel models and/or system design aspects [1–10]. In this paper we focus on outage-limited cooperative channels, where a slow fading model is assumed for both relay and cooperative multiple access (CMA) scenarios. We further impose the half duplex constraint limiting each node to either transmit or receive at any point in time. The primary goal in this setting is to construct strategies that exploit the available *cooperative diversity* with a *reasonable* encoding/decoding complexity. Our work is inspired by the cooperation protocols of Azarian *et al.* in [1]. In particular, for the relay channel we implement a novel variant of the dynamic decode and forward (DDF)

strategy that, through judicious use of orthogonal space-time constellations, reduces the channel seen by the destination to a single-input single-output (SISO) time-selective channel. This variant achieves the excellent diversity-multiplexing tradeoff (DMT) of the DDF protocol [1], while minimizing the decoding complexity at both the relay and the destination nodes. We then present a tree coding/decoding implementation of the optimal cooperative multiple access (CMA) strategy proposed in [1]. This implementation employs the minimum mean square error decision feedback equalizer (MMSE-DFE) Fano decoder [11], to approximate the maximum-likelihood (ML) performance at a much lower complexity. In summary, our contributions in this paper are twofold. First, we establish the practical value of the information-theoretically optimal cooperation protocols proposed in [1]. This goal is accomplished by constructing low complexity lattice coding/decoding implementations of the DDF and CMA cooperation strategies, which are shown to significantly outperform the recently proposed codes by Yang and Belfiore [10]. Second, we elucidate the performance-complexity tradeoff and the parameters controlling it, in different cooperation settings.

The rest of the paper is organized as follows. Section 2 introduces our system model and notations. In Section 3, we briefly review the lattice coding/decoding framework adopted in our work. The proposed coding/decoding schemes for the outage-limited relay channel are detailed in Section 4. Section 5 is devoted to the description of our tree coding/decoding approach for the CMA channel. Finally, we offer some concluding remarks in Section 6.

2 System Model and Notation

In this section, we state the assumptions that apply to the two scenarios considered in this paper (i.e., relay and CMA channels). Assumptions pertaining to a specific channel will be given in the related section. All channels are assumed to be flat Rayleigh-fading and quasi-static, i.e., the channel gains remain constant during one codeword and change independently from one codeword to the next. Furthermore, the channel gains are mutually independent with unit variance. The additive noises at different nodes are zero-mean, mutually-independent, circularly-symmetric, and white complex-Gaussian. The variances of these noises are proportional to one another such that there are always *fixed* offsets between the different signal-to-noise ratios (SNRs). All nodes have the same power constraint, have a single antenna, and operate synchronously. Only the receiving node of any link knows the channel gain; no feedback to the transmitting node is permitted. All cooperating partners operate in the half-duplex mode, i.e., at any point

in time, a node can either transmit or receive, but not both. This constraint is motivated by, e.g., the typically large difference between the incoming and outgoing signal power levels. Next we summarize the notation used throughout the paper.

1. The SNR of a link, ρ , is defined as

$$\rho \triangleq \frac{E}{\sigma^2}, \quad (1)$$

where E denotes the average energy available for transmission of a symbol across the link and σ^2 denotes the variance of the noise observed at the receiving end of the link. We say that $f(\rho)$ is *exponentially equal to ρ^b* , denoted by $f(\rho) \doteq \rho^b$, when

$$\lim_{\rho \rightarrow \infty} \frac{\log(f(\rho))}{\log(\rho)} = b. \quad (2)$$

In (2), b is called the *exponential order* of $f(\rho)$. $\dot{\leq}$ and $\dot{\geq}$ are defined similarly.

2. Assuming that g is a complex Gaussian random variable with zero mean and unit variance, the exponential order of $1/|g|^2$ is defined as

$$v = - \lim_{\rho \rightarrow \infty} \frac{\log(|g|^2)}{\log(\rho)}. \quad (3)$$

The probability density function (PDF) of v has the following property [12]

$$p_v \doteq \begin{cases} \rho^{-\infty} = 0, & \text{for } v < 0, \\ \rho^{-v}, & \text{for } v \geq 0 \end{cases}. \quad (4)$$

3. Consider a family of codes $\{C_\rho\}$ indexed by operating SNR ρ , such that the code C_ρ has a rate of $R(\rho)$ bits per channel use (BPCU) and ML error probability $P_e(\rho)$. For this family, the multiplexing gain r and the diversity gain d are defined as

$$r \triangleq \lim_{\rho \rightarrow \infty} \frac{R(\rho)}{\log \rho}, \quad d \triangleq - \lim_{\rho \rightarrow \infty} \frac{\log(P_e(\rho))}{\log \rho}. \quad (5)$$

4. The problem of characterizing the optimal DMT in a point-to-point communication system over a coherent quasi-static flat Rayleigh-fading channel was posed and solved by Zheng and Tse in [13]. For a MIMO communication system with M transmit and N receive antennas, they showed that, for any $r \leq \min\{M, N\}$, the optimal diversity gain $d^*(r)$ is given by the piecewise linear function joining the (r, d) pairs $(k, (M-k)(N-k))$ for $k = 0, \dots, \min\{M, N\}$, provided that the code-length l satisfies $l \geq M + N - 1$.

5. We say that protocol A *uniformly dominates* protocol B if, for any multiplexing gain r , $d_A(r) \geq d_B(r)$.
6. We say that protocol A is *Pareto optimal*, if there is no protocol B that dominates protocol A in the Pareto sense. Protocol B is said to dominate protocol A in the Pareto sense if there is some r_0 for which $d_B(r_0) > d_A(r_0)$, but no r such that $d_B(r) < d_A(r)$.
7. We denote the ratio of the destination variance to that of inter-user noise variance by c , i.e., $c = \sigma_v^2 / \sigma_w^2$.
8. Throughout the sequel, vectors are denoted by bold lowercase characters (e.g., $\mathbf{x}$), and matrices are denoted by bold uppercase characters (e.g., $\mathbf{H}$). $\mathbb{Z}$, $\mathbb{R}$, $\mathbb{C}$ refer to the ring of integers, field of real numbers, and field of complex numbers, respectively. We refer to the identity matrix of dimension M as $\mathbf{I}_M$ and Kronecker product by $\otimes$. We also use $(x)^+$ to mean $\max\{x, 0\}$, $(x)^-$ to mean $\min\{x, 0\}$ and $\lceil x \rceil$ to mean nearest integer to x towards plus infinity.

3 Lattice Coding and Decoding

An m -dimensional lattice $\Lambda \subset \mathbb{R}^m$ is the set of points

$$\Lambda = \{\boldsymbol{\lambda} = \mathbf{G}\mathbf{u} : \mathbf{u} \in \mathbb{Z}^m\} \quad (6)$$

where $\mathbf{G} \in \mathbb{R}^{m \times m}$ is the lattice generator matrix. Let $\boldsymbol{\eta} \in \mathbb{R}^m$ be a vector and $\mathcal{R}$ a measurable region in $\mathbb{R}^m$ then a lattice code $\mathcal{C}(\Lambda, \boldsymbol{\eta}, \mathcal{R})$ is defined as the set of points of the lattice translate $\Lambda + \boldsymbol{\eta}$ inside the *shaping region* $\mathcal{R}$ [14], i.e.,

$$\mathcal{C}(\Lambda, \boldsymbol{\eta}, \mathcal{R}) = \{\Lambda + \boldsymbol{\eta}\} \cap \mathcal{R}. \quad (7)$$

Here, we focus on construction “A” lattice codes [15]. In this construction, $\Lambda = C + Q\mathbb{Z}^m$ with $C \subseteq \mathbb{Z}_Q^m$ being a linear code over $\mathbb{Z}_Q$ and Q is a prime. The generator matrix of Λ is given by

$$\mathbf{G} = \begin{bmatrix} \mathbf{I} & \mathbf{0} \\ \mathbf{P} & Q\mathbf{I} \end{bmatrix}, \quad (8)$$

where $[\mathbf{I}, \mathbf{P}^T]^T$ is the generator matrix of C (in a systematic form) [15]. The shaping region $\mathcal{R}$ of the lattice code $\mathcal{C}(\Lambda, \boldsymbol{\eta}, \mathcal{R})$ can be 1) the m -dimensional sphere, 2) the fundamental Voronoi region of a sublattice $\Lambda' \subset \Lambda$, or 3) the m -dimensional hypercube. These three alternatives provide a tradeoff between

performance and encoding complexity. The spherical shaping approach yields the maximum shaping gain but suffers from the largest encoding complexity. Encoding is typically done via look-up tables which limits this approach to short block lengths (since the number of entries in the table grows exponentially with the block length). Voronoi shaping offers a nice compromise between performance and complexity. In this approach, the encoding complexity is equivalent to that of m -dimensional vector quantization which, loosely speaking, ranges from polynomial to linear (in the block length) based on the choice of the shaping lattice. On the other hand, with large enough m and the appropriate choice of Λ' , the shaping gain approaches that of the sphere. The third alternative, i.e., hypercubic shaping, allows for the lowest encoding complexity, however, at the expense of a performance loss (i.e., the worst shaping gain). As a side benefit, hypercubic shaping also minimizes the peak-to-average power ratio. The final ingredient in lattice coding is the translate vector $\boldsymbol{\eta}$ which is used to maximize the number of lattice points inside $\mathcal{R}$ and/or randomize the distribution of the codebook over $\mathcal{R}$ [14, 16]. In fact, Voronoi coding with $\boldsymbol{\eta}$ uniformly distributed over the Voronoi cell of Λ' corresponds to the mod- Λ approach of Erez and Zamir [16]. The proposed coding approaches in our work can be coupled with any shaping technique and any choice for the translate $\boldsymbol{\eta}$. The optimization of these parameters is beyond the scope of this paper, and hence, will not be considered further. For simplicity of presentation, and implementation, we will focus in our simulation study on hypercubic shaping.

The primary appeal of lattice codes, in our framework, stems from their amenability to a low complexity decoding architecture, as argued in the sequel. For decoding purposes, we express $\mathcal{C}(\Lambda, \boldsymbol{\eta}, \mathcal{R})$ as the set of points $\mathbf{x}$ given by

$$\mathbf{x} = \mathbf{G}\mathbf{u} + \boldsymbol{\eta}, \quad \text{for } \mathbf{u} \in \mathcal{U} \quad (9)$$

where $\mathcal{U} \subset \mathbb{Z}^m$ is the code *information set*. Assuming that the code is used over a linear Gaussian channel, then the input-output relation is given by

$$\mathbf{r} = \mathbf{H}\mathbf{x} + \mathbf{z} \quad (10)$$

where $\mathbf{r} \in \mathbb{R}^n$ denotes the received signal vector, $\mathbf{z} \sim \mathcal{N}(\mathbf{0}, \sigma^2 \mathbf{I})$ is the AWGN vector, and $\mathbf{H} \in \mathbb{R}^{n \times m}$ is a matrix that defines the channel linear mapping. In the coherent paradigm, where $\mathbf{H}$ is known to the receiver, the maximum likelihood (ML) decoding rule reduces to

$$\hat{\mathbf{u}} = \arg \min_{\mathbf{u} \in \mathcal{U}} \|\mathbf{r} - \mathbf{H}\boldsymbol{\eta} - \mathbf{H}\mathbf{G}\mathbf{u}\|^2 \quad (11)$$

The optimization problem in (11) can be viewed as a *constrained* version of the closest lattice point search (CLPS) with lattice generator matrix given by $\mathbf{H}\mathbf{G}$ and constraint set $\mathcal{U}$ [11]. This observation inspired the

class of *sphere decoding* algorithms (e.g., [17]). More recently, a unified tree search decoding framework which encompasses the sphere decoders as special cases was proposed in [11]. Of particular interest to our work here is the (MMSE-DFE) Fano decoder discovered in [11]. In this decoder, we first *preprocess* the channel matrix via the feedforward filter of the MMSE-DFE then we apply the celebrated Fano tree search algorithm to identify the closest lattice point. In particular, we attempt to approximate the optimal solution for

$$\hat{\mathbf{u}} = \arg \min_{\mathbf{u} \in \mathbb{Z}^m} |\mathbf{F}(\mathbf{r} - \mathbf{H}\boldsymbol{\eta} - \mathbf{H}\mathbf{G}\mathbf{u})|^2, \quad (12)$$

where $\mathbf{F}$ is the feedforward filter of the MMSE-DFE. It is important to note the expanded search space in (12), i.e., we replaced $\mathcal{U}$ in (11) with $\mathbb{Z}^m$. Relaxing this constraint results in a significant complexity reduction since enforcing the boundary control $\mathbf{u} \in \mathcal{U}$ can be computationally intensive for non-trivial lattice codes [11]. While the search space expansion is another source for sub-optimality, it was shown in [11, 18] that the loss in performance is very marginal **only** when the MMSE-DFE preprocessing is employed (i.e., with $\mathbf{F} = \mathbf{I}$ one would see a significant performance loss).

One of our main contributions is showing that the MMSE-DFE Fano decoder yields an excellent performance-vs-complexity tradeoff when appropriately used in cooperative channels. For more details about this decoder, the reader is referred to [11].

4 The Relay Channel

For exposition purposes, we limit our discussion to the single relay scenario. The proposed techniques, however, extend naturally to channels with an arbitrary number of relays.

4.1 Amplify and Forward (AF) Cooperation

In [1], the non-orthogonal amplify and forward (NAF) strategy was shown to achieve the optimal DMT within the class of AF protocols. In NAF relaying, the source transmits on every symbol-interval in a cooperation frame, where a cooperation frame is defined as two consecutive symbol-intervals. The relay, on the other hand, transmits only once per cooperation frame; it simply repeats the (noisy) signal it observed during the previous symbol-interval. It is clear that this design is dictated by the half-duplex constraint, which implies that the relay can repeat at most once per cooperation frame. We denote the

repetition gain by b and, for frame k , the information symbols are denoted by $\{x_{j,k}\}_{j=1}^2$. The signals received by the destination during frame k are given by:

$$y_{1,k} = g_1 x_{1,k} + v_{1,k}, \quad (13)$$

$$y_{2,k} = g_1 x_{2,k} + g_2 b(h x_{1,k} + w_{1,k}) + v_{2,k}. \quad (14)$$

Note that, in order to decode the message, the destination needs to know the relay repetition gain b , the source-relay channel gain h , the source-destination channel gain g_1 , and the relay-destination channel gain g_2 . The following result from [1] states the DMT achieved by this protocol.

Theorem 1 *The diversity-multiplexing tradeoff achieved by the NAF relay protocol is*

$$d(r) = 1 - r + (1 - 2r)^+. \quad (15)$$

In [1], the achievability of (15) was established using a long Gaussian codebook which spans infinitely many cooperation frames (with the same channel coefficients). More recently, Yang and Belfiore have proposed a novel scheme that achieves the tradeoff in (15) by only coding over one cooperation frame. Yang and Belfiore design is inspired by the fact that the input-output relationship in (13) and (14) corresponds to the following 2×2 MIMO channel

$$\mathbf{y} = \begin{bmatrix} g_1 & 0 \\ \sqrt{\frac{c}{|g_2 b|^2 + c}} g_2 b h & \sqrt{\frac{c}{|g_2 b|^2 + c}} g_1 \end{bmatrix} \mathbf{x} + \mathbf{z} \quad (16)$$

where $\mathbf{z} \in \mathbb{C}^2$ is the noise vector with circularly symmetric i.i.d. Gaussian components, $z_i \sim \mathcal{N}_C(0, \sigma_v^2)$. One can then use any of the 2×2 linear dispersion (LD) constellations [19] as a cooperation scheme in this setup. A 2×2 LD constellation is obtained by multiplying a 4-dimensional QAM vector $\mathbf{u}$ by a generator matrix. As shown in [10], by setting the generator matrix to that of the so called Golden constellation, i.e.,

$$\mathbf{G}_{gc} = \frac{1}{\sqrt{5}} \begin{bmatrix} \alpha & \alpha\theta & 0 & 0 \\ 0 & 0 & i\bar{\alpha} & i\bar{\alpha}\bar{\theta} \\ 0 & 0 & \alpha & \alpha\theta \\ \bar{\alpha} & \bar{\alpha}\bar{\theta} & 0 & 0 \end{bmatrix}$$

where $\theta = \frac{1+\sqrt{5}}{2}$, $\bar{\theta} = 1 - \theta$, $\alpha = 1 + i\bar{\theta}$ and $\bar{\alpha} = 1 + i\theta$, one can use the non-vanishing determinant property to establish the achievability of (15) by this scheme. The lattice decoding framework, adopted here, can be applied to this approach by applying the appropriate scaling factor and separating the real and

imaginary parts of the received signal. This reduces (15) to our model in (10) where $\mathcal{U} = \mathbb{Z}_Q^8$ corresponds to an input Q^2 -QAM constellation.

In applications where the code word is allowed to span multiple cooperation frames, Yang and Belfiore Golden constellation fails to exploit the long block length in improving the coding gain. By appealing to the lattice coding framework, one can improve the coding gain while still using the same decoder. For example, we can concatenate the inner Golden constellation with an outer trellis code whose constraint length is allowed to increase with the block length. The improved coding gain of this approach translated into enhanced frame error rates (as validated by the numerical results in Section 4.3). In our design, we generate our trellis code as a systematic convolutional code (CC) over $\mathbb{Z}_Q$. Assuming that one code word spans N cooperation frames, the received vector can now be expressed as

$$\mathbf{y} = \mathbf{H}\mathbf{G}'_{gc}\mathbf{x} + \mathbf{z} \quad (17)$$

$$= \mathbf{H}\mathbf{G}'_{gc}(\mathbf{G}_{cc}\mathbf{u} + \boldsymbol{\eta}) + \mathbf{z} \quad (18)$$

where $\mathbf{x} \in \mathbb{R}^{2N}$ is the output of the CC, and $(\mathbf{H}\mathbf{G}_{gc})$ is the effective channel seen by the CC. This effective channel is obtained as follows: $\mathbf{H}$ is the real representation of the 2×2 MIMO channel in (16), and $\mathbf{G}'_{gc} = \mathbf{I}_{N/2} \otimes \mathbf{G}_{gc}^{(r)}$ where $\mathbf{G}_{gc}^{(r)} \in \mathbb{R}^{8 \times 8}$ is real representation of the Golden constellation generator matrix in (17). The model in (18) is based on observing that the CC can be viewed as a construction A lattice code with hypercubic shaping and a generator matrix $\mathbf{G}_{cc}$. Now, we multiply by the feedforward filter $\mathbf{F}$ of the MMSE-DFE for the effective channel $(\mathbf{H}\mathbf{G}_{gc})$ and then use Fano search algorithm on the composite channel-code generator matrix $\mathbf{F}\mathbf{H}\mathbf{G}_{gc}\mathbf{G}_{cc}$.

4.2 Decode and Forward (DF) Cooperation

To the best of our knowledge, within the class of DF strategies, the dynamic decode and forward (DDF) achieves the best DMT [1] (the same protocol was independently discovered in different contexts [20, 21]). This motivates developing low complexity variants of this strategy which are particularly suited for implementation. We take a step by step approach where a number of lemmas, that characterize the modifications needed for complexity reduction while maintaining a good performance, are derived. For the sake of completeness, we first describe the DDF protocol.

In the DDF protocol the source transmits data, at a rate of R bits per channel use (BPCU), during every symbol-interval in the codeword. A codeword is defined as M consecutive sub-blocks, during which all channel gains remain fixed. Each sub-block is composed of T symbol-intervals. The relay listens to the

source for enough sub-blocks until the mutual information between its received signal and source signal exceeds NTR . It then decodes and re-encodes the message using an independent Gaussian code-book and transmits it during the rest of the codeword. We denote the signals transmitted by the source and relay by $\{x_k\}_{k=1}^{MT}$ and $\{\tilde{x}_k\}_{k=M'T+1}^{MT}$, respectively, where N' is the number of sub-blocks that the relay waits before starting transmission. Using this notation, the received signals (at the destination) can be written as

$$y_k = \begin{cases} g_1 x_k + v_k & \text{for } N'T \geq k \geq 1 \\ g_1 x_k + g_2 \tilde{x}_k + v_k & \text{for } NT \geq k > M'T \end{cases},$$

where g_1 and g_2 denote the source-destination and relay-destination channel gains, respectively. It is now clear that the number of sub-blocks that the relay listens, should be chosen according to

$$M' = \min \left\{ M, \left\lceil \frac{MR}{\log_2(1 + |h|^2 c \rho)} \right\rceil \right\}, \quad (19)$$

where h is the source-relay channel gain. In this expression, $c = \sigma_v^2 / \sigma_w^2$ denotes the ratio of the destination noise variance, to that of the relay. The following result from [1], describes the DMT achievable by the DDF protocol as $T \rightarrow \infty$ and $M \rightarrow \infty$.

Theorem 2 *The diversity-multiplexing tradeoff achieved by the DDF protocol is given by*

$$d(r) = \begin{cases} 2(1-r) & \text{if } \frac{1}{2} \geq r \geq 0 \\ (1-r)/r & \text{if } 1 \geq r \geq \frac{1}{2} \end{cases}. \quad (20)$$

It is evident from the protocol description that the achievability result in [1] relied on using independent Gaussian codebooks at the source and relay nodes. This approach will potentially require a computationally intensive algorithm at the destination to implement *joint* decoding for the source and relay signals. Allowing the relay node to start transmission at the beginning of every sub-block, based on the value of the instantaneous mutual information, is another potential source for complexity. In practice, this requires the source to use a very high-dimensional constellation (with a very low rate code) such that the information stream is uniquely decodable from one sub-block if the source-relay channel is good enough. This feature also impacts the amount of overhead in the relay-destination packet since the destination must be informed with the starting time of relay transmission. Now, we introduce two simplifications of the original DDF protocol that aim to lower the complexities associated with these two properties.

1. After successfully decoding, the relay can correctly anticipate the future transmissions from the source (i.e., x_k for $M'T + 1 \leq k \leq MT$) since it knows the source codebook. Based on this

knowledge, the relay implements the following scheme, i.e.

$$\tilde{x}_k = \begin{cases} x_{k+1}^* & \text{for } k = M'T + 1, M'T + 3, \dots \\ -x_{k-1}^* & \text{for } k = M'T + 2, M'T + 4, \dots \end{cases}, \text{ and} \quad (21)$$

which reduces the signal seen by the destination for $M'T + 1 \leq k \leq MT$ to an Alamouti constellation.

2. We allow the relay to transmit only after the codeword is halfway through, i.e., we replace the rule in (19) with

$$M' = \min \left\{ M, \max \left\{ \frac{M}{2}, \left\lceil \frac{MR}{\log_2(1 + |h|^2 c \rho)} \right\rceil \right\} \right\}, \quad (22)$$

Fortunately, these modifications do not entail any loss in performance (at least from the DMT perspective) as formalized in the following lemma.

Lemma 3 *The modified (lower complexity) DDF protocol still achieves the same DMT in Theorem 2.*

Proof: To prove the first part of the lemma, let us denote the signals received at the destination by $\{y_k\}_{k=1}^{MT}$. Then

$$y_k = \begin{cases} g_1 x_k + v_k & \text{for } k = 1, \dots, M'T \\ g_1 x_k + g_2 x_{k+1}^* + v_k & \text{for } k = M'T + 1, M'T + 3, \dots \\ g_1 x_k - g_2 x_{k-1}^* + v_k & \text{for } k = M'T + 2, M'T + 4, \dots \end{cases}$$

Now, through linear processing of $\{y_k\}_{k=1}^{MT}$, the destination derives $\{\tilde{y}_k\}_{k=1}^{MT}$ such that

$$\tilde{y}_k = \begin{cases} g_1 x_k + \tilde{v}_k & \text{for } k = 1, \dots, M'T \\ \sqrt{|g_1|^2 + |g_2|^2} x_k + \tilde{v}_k & \text{for } k = M'T + 1, \dots, MT \end{cases}, \quad (23)$$

with $\tilde{v}_k$ being statistically identical to v_k . Using (23), it is straightforward to see that destination pairwise error probability, averaged over the ensemble of Gaussian codes (used by the source) and conditioned on a certain channel realization, is given by

$$P_{PE|g_1, g_2, h} \leq \left(1 + \frac{1}{2}|g_1|^2 \rho\right)^{-M'T} \left(1 + \frac{1}{2}(|g_1|^2 + |g_2|^2) \rho\right)^{-(M-M')T}.$$

This last expression, though, is identical to the one corresponding to the original DDF protocol (refer to [1]). This means that this implementation of the DDF strategy will achieve the same DMT as Theorem 2 as $T \rightarrow \infty$ and $M \rightarrow \infty$ which completes the proof of the first part.

To prove the second part, we notice that the effect of constraining the relay to start transmission only after the codeword is halfway through, i.e., adopting the rule (22), is to replace equation (52) in [1] with

$$\inf_{O^{+,f}} u = \begin{cases} 0 & \text{if } f = \frac{1}{2} \\ (1 - \frac{r}{f})^+ & \text{if } 1 \geq f > \frac{1}{2} \end{cases}, \quad (24)$$

where u denotes the exponential order of $1/|h|^2$. Now, since (24) is different from (52) in [1] only for $f = 1/2$, for which $\inf(v_1 + v_2)$ is already equal to the optimal value $2(1 - r)$, we conclude that this restriction does not affect the DMT achieved by the protocol. $\square$

As shown in (23), the channel seen by the destination in the modified DDF protocol is a time-selective SISO which facilitates leveraging standard SISO decoding architectures (e.g., belief propagation, Fano decoder) at the destination. In addition, by restricting the relay to transmit only after $M' \geq M/2$ means that the constellation size can be chosen such that the information stream is uniquely decodable only after $M' = M/2$.

The next result investigates the effect of allowing the relay to transmit only at a finite number of instants. These instants partition the code word into $N + 1$ segments which are not necessarily equal in length. We assume that the j -th segment starts at the beginning of sub-block $N_j + 1$, denote the set of fractions $\{f_j\}_{j=1}^N$ by to N waiting fractions f_j such that $f_j \triangleq \frac{N_j}{N}$ with $f_0 \triangleq 0$ and $f_{N+1} \triangleq 1$. Thus

$$f_0 \triangleq 0 < f_1 < \dots < f_N < f_{N+1} \triangleq 1.$$

The question now is how to choose $\{f_j\}_{j=1}^N$, for a finite N , such that the protocol achieves the *optimal* DMT. The following lemma shows that this problem does not have a unique optimal solution and characterizes a Pareto optimal set of fractions.

Lemma 4 *For the DDF protocol with a finite N ,*

1. *there exists no uniformly dominant set of fractions $\{f_j^u\}_{j=1}^N$.*
2. *let $f_1^p = \frac{1}{2}$ and*

$$f_j^p = \frac{1 - f_{j-1}^p}{2 - (1 + \frac{1}{f_N^p})f_{j-1}^p}, \text{ for } N \geq j > 1 \quad (25)$$

then the set of fractions $\{f_j^p\}_{j=1}^N$ is Pareto optimal, with

$$d^p(r) = 1 - r + (1 - \frac{r}{f_N^p})^+. \quad (26)$$

Proof: We note that the outage set for the DDF protocol with a general set of waiting fractions, $\{f_j\}_{j=1}^N$, is still given by equation (49) in [1], i.e.

$$O^+ = \{(v_1, v_2, u) \in \mathbb{R}^{3+} | f(1 - v_1)^+ + (1 - f)(1 - \min\{v_1, v_2\})^+ \leq r\}.$$

The only difference is that f is now given by (compare with (52) of [1])

$$f = \begin{cases} f_1 & \text{if } 1 - \frac{r}{f_1} > u \geq 0 \\ f_j & \text{if } 1 - \frac{r}{f_j} > u \geq (1 - \frac{r}{f_{j-1}})^+ \\ 1 & \text{if } u \geq (1 - \frac{r}{f_N})^+ \end{cases} . \quad (27)$$

Next, we split O^+ such that

$$O^+ = \cup_{j=1}^{N+1} O_j^+, \text{ where } O_j^+ = \{(v_1, v_2, u) \in O^+ | f = f_j\}. \quad (28)$$

Now, from (27) and (28) we get

$$\inf_{O_j^+} u = \begin{cases} 0 & \text{for } j = 1 \\ (1 - \frac{r}{f_{j-1}})^+ & \text{for } N + 1 \geq j > 2 \end{cases} .$$

Also, since $f_j \geq \frac{1}{2}$, we have $\inf_{(v_1, v_2) \in O_j^+} (v_1 + v_2) = (1 - r)/f_j$ (refer to (55) in [1]). Thus

$$\begin{aligned} d_j(r) &\triangleq \inf_{O_j^+} (v_1 + v_2 + u), \\ d_j(r) &= \frac{1 - r}{f_j} + (1 - \frac{r}{f_{j-1}})^+. \end{aligned} \quad (29)$$

But, (28) along with (29) results in

$$\begin{aligned} d(r) &= \min_{f_j \geq r} d_j(r), \\ d(r) &= \min_{f_j \geq r} \frac{1 - r}{f_j} + (1 - \frac{r}{f_{j-1}})^+. \end{aligned} \quad (30)$$

Now let us assume that the set of waiting fractions $\{f_j^u\}_{j=1}^N$ is uniformly optimal. Pick $\{f_j\}_{j=1}^N$ such that $f_N^u < f_N < 1$. Then from (30) we conclude that for any $f_N^u < r < f_N$, $d^u(r) = 1 - r$ and $d(r) = 1 - r + 1 - r/f_N$. Thus $d^u(r) < d(r)$, which is in contradiction with the uniform optimality assumption of $\{f_j^u\}_{j=1}^N$. To prove the second part of the lemma, we observe that for $N \geq j \geq 1$, $\{f_j^p\}_{j=1}^N$ as given by (25) results in

$$d_{N+1}^p(r) < d_j^p(r), \text{ for } f_j \geq r \geq 0, r \neq f_{j-1} \quad (31)$$

and

$$\begin{aligned} d_{N+1}^p(f_{j-1}) &= d_j^p(f_{j-1}), \text{ or} \\ d_{N+1}^p(f_{j-1}) &= \frac{1 - f_{j-1}}{f_j}. \end{aligned} \quad (32)$$

Now (31), along with (30) and (29) proves that $\{f_j^p\}_{j=1}^N$ achieves (26). The only thing left is to show that $d^p(r)$ is indeed Pareto optimal, i.e., no other set $\{f_j\}_{j=1}^N$ dominates $\{f_j^p\}_{j=1}^N$, in the Pareto sense. To do so, we assume such a set exists and observe that since $f_0 = f_0^p = 0$ and $f_{N+1} = f_{N+1}^p = 1$, there should be $N + 1 \geq i \geq 1$ and $N + 1 \geq \ell \geq 1$ such that

$$f_{i-1} \leq f_{\ell-1}^p < f_\ell^p < f_i, \text{ or} \quad (33)$$

$$f_{i-1} < f_{\ell-1}^p < f_\ell^p \leq f_i. \quad (34)$$

Now, if (33) is true, then we observe from (30) that

$$d(f_{\ell-1}^p) \leq d_i(f_{\ell-1}^p) = \frac{1 - f_{\ell-1}^p}{f_i} < \frac{1 - f_{\ell-1}^p}{f_\ell^p} = d^p(f_{\ell-1}^p),$$

where we have used (32) in deriving the last step. This, however is in contradiction with the Pareto dominance of $\{f_j^p\}$, since

$$d(f_{\ell-1}^p) < d^p(f_{\ell-1}^p).$$

On the other hand, if (34) is true, then

$$d(f_{i-1}) \leq d_i(f_{i-1}) = \frac{1 - f_{i-1}}{f_i} < 2 - (1 + \frac{1}{f_N^p})f_{i-1} = d^p(f_{i-1}),$$

or

$$d(f_{i-1}) < d^p(f_{i-1}),$$

which again is in contradiction with Pareto dominance of $\{f_j^p\}$. This completes the proof of the second part. $\square$

Figure 2 shows the DMT for Pareto optimal DDF protocols with $N = 1(\{\frac{1}{2}\})$, $N = 2(\{\frac{1}{2}, \frac{2}{3}\})$ and $N = \infty$.

4.3 Numerical Results

Throughout this section, we consider construction-A lattice codes obtained from systematic convolutional codes (CC) over $\mathbb{Z}_Q$ with Q a prime number. Unless otherwise mentioned, we choose the SNR level of the inter-user channel to be 3 dB higher than the SNR at the destination. In all scenarios, the MMSE-DFE Fano decoder uses a bias $b = 1.2$ and a step-size $\Delta = 5$ [22].

First, we demonstrate the performance improvement obtained by augmenting the Golden constellation of [10] with a lattice code obtained from a rate $1/2$ systematic CC. In both schemes, the frame length is 128. We assume that the source and the relay transmit with equal power, and that the source transmits with same power at all instants. Figure 1 shows the frame error rate (FER) of the two coding schemes as a function of the average received SNR at the destination. For the Golden constellation, 4-QAM, 16-QAM and 64-QAM modulations for the information symbols lead to transmission rates of 2, 4 and 6 BPCU, respectively. For comparison, we use primes $Q = 5, 17$ and 67 , resp., to achieve the corresponding transmission rates (slightly higher though). From the figure, we see that augmenting the Golden constellation with the CC provides performance improvement of about 1 – 1.5 dB. The inferior performance of the augmented code for the 2 BPCU is due to the fact that the effective transmission rate of the code, i.e., $\log_2(5) = 2.32$, is significantly higher than 2 BPCU offered by Golden constellation. This choice is dictated by the need to choose Q as a prime so we have a nice lattice representation for the received signal which is instrumental for the MMSE-DFE Fano decoder.

Next, we proceed to the modified DDF protocol proposed in Section 4.2. At the source, the information stream is appended with 16 CRC bits, and the resulting vector is encoded using a rate $1/4$ systematic CC. The relay attempts decoding after waiting N_i sub-blocks, where N_i is the smallest among the set of allowed waiting times such that the mutual information at the relay exceeds the received rate. In order to avoid error propagation at the destination, the decoded vector is checked for validity using the CRC bits. If the decoder vector is valid, i.e., it satisfies the CRC check, then the relay uses the modified DDF protocol. If the decoded stream at the relay does not satisfy the CRC check, then the relay attempts decoding again at the next allowed waiting time (N_{i+1}), and so on. At the receiver we use the MMSE-DFE Fano decoder (note that the MMSE-DFE part is now a trivial scaling since the channel seen by the destination is SISO). We also assume that the destination knows the time at which the relay starts transmitting (via overhead bits). For the range of transmission rates considered in the sequel, it turns out that increasing the number of segments beyond 3 provides negligible increase in performance. Figure 3 shows the outage probability

of DDF relay protocol, when the codeword partitioned into 3, 4, 5 and 6 segments. As seen from the figure, the gap between the outage curves is negligible. Therefore, in the sequel, we consider only the variant of DDF relay protocol with 3 segments. Moreover, we choose the waiting fractions f_i according to Lemma 4, *i.e.*, the pareto-optimal set of waiting fractions for 3 segments, given by $\{\frac{1}{2}, \frac{2}{3}\}$. Figure 4 compares the performance of our variant of the DDF protocol with that of the NAF protocol for 2 and 3 BPCU. The proposed DDF strategy offers a gain of about 4 dB(and about 6 dB) over the NAF scheme, for 2(and 3) BPCU. Note, however, that the DDF protocol entails an complexity at the relay, as compared with the NAF protocol, since the relay needs to decode the information stream. Finally, we note that although several implementations of Amplify-and-Forward and Decode-and-Forward variants exist ([5], [7], [6]), all these works consider low transmission rates. However, the impact of superior DMTs of our schemes does lead to significantly better performance at low transmission rates. It should be noted, however, that the difference in performance between the protocols that are spectrally efficient and those that are not manifests itself only at high transmission rate scenarios. Therefore, we focus on high transmission rates in this paper.

5 The Cooperative Multiple Access (CMA) Channel

In this section, we implement the CMA-NAF protocol for two users. We start with describing the protocol. In the CMA-NAF protocol, each of the two sources transmits once per cooperation frame, where a cooperation frame is defined by two consecutive symbol-intervals. Each source, when active, transmits a linear combination of the symbol it intends to send and the (noisy) signal it received from its partner during the last symbol-interval. For source j and frame k , we denote the broadcast and repetition gains by a_j and b_j , respectively, the symbol to be send by $x_{j,k}$, and the transmitted signal by $t_{j,k}$. At startup the transmitted signals will take the form

$$t_{1,1} = a_1 x_{1,1} \tag{35}$$

$$t_{2,1} = a_2 x_{2,1} + b_2 (h t_{1,1} + w_{2,1}) \tag{36}$$

$$t_{1,2} = a_1 x_{1,2} + b_1 (h t_{2,1} + w_{1,1}) \tag{37}$$

$$t_{2,2} = a_2 x_{2,2} + b_2 (h t_{1,2} + w_{2,2}) \tag{38}$$

where h denotes the inter-source channel gain and $w_{j,k}$ the noise observed by source j during the frame k . (We assume that $w_{j,k}$ has variance σ_w^2 .) The corresponding signals received by the destination are

$$y_{1,1} = g_1 t_{1,1} + v_{1,1} \quad (39)$$

$$y_{2,1} = g_2 t_{2,1} + v_{2,1} \quad (40)$$

$$y_{1,2} = g_1 t_{1,2} + v_{1,2} \quad (41)$$

$$y_{2,2} = g_2 t_{2,2} + v_{2,2} \quad (42)$$

where g_j is the gain of the channel connecting source j to the destination and $v_{j,k}$ the destination noise of variance σ_v^2 . Note that, as mandated by our half-duplex constraint, no source transmits and receives simultaneously. The broadcast and repetition gains $\{a_j, b_j\}$ are (experimentally) chosen to minimize outage probability at the destination. As a consequence of symmetry, a_1 and a_2 , as well as b_1 and b_2 , will have the same optimal value. Thus, we assume that broadcast and repetition gains are the same at each source and omit the subscripts, yielding $\{a, b\}$. We also define a codeword as N consecutive symbol-intervals (assuming that N is even, this means that there are $N/2$ cooperation frames in each codeword). The following result from [1] gives the diversity-multiplexing tradeoff achieved by this protocol.

Theorem 5 *The CMA-NAF protocol achieves the optimal diversity-multiplexing tradeoff of the channel, i.e., for two users*

$$d(r) = 2(1 - r). \quad (43)$$

From (35-42), the received vector at the destination can be written as

$$\mathbf{y}_1 = \mathbf{H}_1 \mathbf{x}_1 + \mathbf{B} \mathbf{w} + \mathbf{v}, \quad (44)$$

where $\mathbf{y} = [y_{2,N} \ y_{1,N} \ \dots \ y_{2,1} \ y_{1,1}]^T \in \mathbb{C}^N$ is the vector observed at the destination, $\mathbf{x}_1 = [x_{2,N} \ x_{1,N} \ \dots \ x_{2,1} \ x_{1,1}]^T \in \mathbb{C}^N$ is the vector formed by multiplexing the codewords transmitted by the two sources, $\mathbf{w} \in \mathbb{C}^{N-1}$ and $\mathbf{v} \in \mathbb{C}^N$ are the AWGN vectors at the sources and the destination, respectively. The effective channel matrix, $\mathbf{H}_1 \in \mathbb{C}^{N \times N}$ is the upper triangular matrix

$$\mathbf{H}_1 = a \mathbf{D}_g \begin{bmatrix} 1 & (bh) & \dots & (bh)^N \\ & 1 & \dots & (bh)^{N-1} \\ & & \ddots & \vdots \\ & & & 1 \end{bmatrix}$$

where $\mathbf{D}_g = \text{diag}(g_2, g_1, g_2, \dots, g_2, g_1)$. Similarly, $\mathbf{B} \in \mathbb{C}^{N \times (N-1)}$ is given by

$$\mathbf{B} = b\mathbf{D}_g \begin{bmatrix} 1 & (bh) & \dots & (bh)^{N-1} \\ & 1 & \dots & (bh)^{N-2} \\ & & \ddots & \vdots \\ & & & 1 \\ & & & 0 \end{bmatrix}$$

The noise $(\mathbf{B}\mathbf{w} + \mathbf{v})$ in (44) is colored, and must be whitened before tree search with the MMSE-DFE Fano decoder can be performed. Let $\Sigma = \sigma_w^2 \mathbf{B}\mathbf{B}^H + \sigma_v^2 \mathbf{I}$ be the covariance matrix of $(\mathbf{B}\mathbf{w} + \mathbf{v})$. Then,

$$\mathbf{y}^c = \mathbf{H}^c \mathbf{x}_1^c + \Sigma^{-\frac{1}{2}} (\mathbf{B}\mathbf{w} + \mathbf{v}) \quad (45)$$

where $\mathbf{y}^c = \Sigma^{-\frac{1}{2}} \mathbf{y}_1$, $\mathbf{H}^c = \Sigma^{-\frac{1}{2}} \mathbf{H}_1$ and the noise vector $\mathbf{z}^c = \Sigma^{-\frac{1}{2}} (\mathbf{B}\mathbf{w} + \mathbf{v})$ now consists of *i.i.d* Gaussian components with variance 1. $\Sigma^{-\frac{1}{2}}$ may be computed by any of the standard methods, *i.e.*, singular value decomposition, Cholesky decomposition or QR decomposition. The input-output relation in (45) can now be written in the standard form (10) by separating the real and imaginary parts, to obtain the real $2N \times 2N$ system:

$$\mathbf{y} = \mathbf{H}\mathbf{x} + \mathbf{z} \quad (46)$$

We construct the generator matrix $\mathbf{G}$ of the two sources combined, as seen by the decoder, by appropriately multiplexing the rows and columns of the lattice generators of the two sources, $\mathbf{G}_1$ and $\mathbf{G}_2$. Fano decoding can now be done over the resulting joint channel-code lattice, after MMSE-DFE preprocessing of the channel matrix $\mathbf{H}$. Finally, the decoded codewords of the two sources are obtained by demultiplexing the decoded lattice point.

5.1 Numerical Results

In this section, we compare the performance of the lattice coded CMA-NAF scheme with that of other schemes. The frame length is chosen to be $N = 128$. Each user encodes its information stream using a construction-A lattice code obtained from a systematic convolutional code over $\mathbb{Z}_Q$. At the destination, MMSE-DFE Fano decoding is performed over the joint code-channel lattice of both the users. We define the frame error event as $\{(\hat{\mathbf{x}}_1, \hat{\mathbf{x}}_2) \neq (\mathbf{x}_1, \mathbf{x}_2)\}$, where $\hat{\mathbf{x}}_1$ and $\hat{\mathbf{x}}_2$ refer to the decoded codewords. Figure 5 shows the frame error rate of the lattice coded CMA-NAF protocol vs. when the two sources cooperate according to NAF relay protocol. We show the performance for 2 and 4 BPCU, and the coding scheme

achieving the better performance (Golden constellation alone/Golden constellation+CC) is chosen for the NAF relay protocol. Figure 5 also shows the frame error rate of the CMA-NAF protocol, when both sources use uncoded QAM constellations for transmission. As in Figure 1, the worse performance of lattice coded CMA-NAF *w.r.t* uncoded QAM can be explained by the higher transmission rate of the lattice code (with $Q = 5$). Both coded and uncoded transmission with CMA-NAF protocol perform significantly better than the NAF-relay protocol. The performance gap between the two schemes widens as the transmission rate increases, which can be explained by the superior DMT of the CMA-NAF protocol over the NAF-relay protocol. Figure 6 shows the bit error rate performance of uncoded QAM transmission with CMA-NAF protocol, vs. NAF-relay protocol with the Golden constellation. Again, CMA-NAF protocol with uncoded transmission shows bit error rate improvement of about 3 dB at 2 BPCU, and about 5 dB at 4 BPCU. Finally, Figures 7 and 8 show the performance and complexity trade-off of the MMSE-DFE Fano decoder *w.r.t* bias for the CMA NAF protocol with CC lattice coded transmission (for $N = 64$). We see from the figures that complexity of the Fano decoder can be reduced at the expense of complexity. In our simulations, we use $b = 1.2$ to achieve good performance with reasonable complexity.

6 Conclusions

We have developed a lattice theoretic framework for cooperative coding in half-duplex outage-limited channels. This framework achieves the cooperative diversity gains promised in [1] and enjoys realizable encoding and decoding complexity. In the relay channel, the proposed scheme achieves the optimal diversity-multiplexing tradeoff for $r \leq 0.5$ while reducing the channel between the source and relay, on one side, and the destination, on the other side, to a time selective SISO channel. This simplification allows for using traditional receiver architectures in this scenario. A tree coding approach that achieves the optimal diversity-multiplexing for the cooperative multiple access channels is developed. In this context, the MMSE-DFE Fano decoder is shown to yield an excellent performance-vs-complexity tradeoff. The significant performance gains offered by the proposed schemes are validated via a comprehensive simulation study.

References

- [1] K. Azarian, H. E. Gamal, and P. Schniter, "On the achievable diversity-multiplexing tradeoff in half duplex cooperative channels," *IEEE Trans. Inform. Theory*, vol. 51, pp. 4152–4172, Dec. 2005.
- [2] A. Sendonaris, E. Erkip, and B. Aazhang, "User cooperation diversity. part I. system description," *IEEE Trans. Communications*, Nov. 2003.
- [3] A. Sendonaris, E. Erkip, and B. Aazhang, "User cooperation diversity. part II. implementation aspects and performance analysis," *IEEE Trans. Communications*, Nov. 2003.
- [4] J. N. Laneman, D. N. C. Tse, and G. W. Wornell, "Cooperative diversity in wireless networks: Efficient protocols and outage behavior," *IEEE Trans. Info. Theory*, vol. 50, pp. 3062–3080, Dec. 2004.
- [5] A. Stefanov and E. Erkip, "Cooperative space-time coding for wireless networks," *IEEE Trans. Communications*, vol. 53, pp. 1804–1809, Nov. 2005.
- [6] M. Janani, A. Hedayat, T. E. Hunter, and A. Nosratinia, "Coded cooperation in wireless communications: space-time transmission and iterative decoding," *IEEE Trans. Signal Processing*, vol. 52, pp. 362–371, Feb. 2004.
- [7] Z. Zhang and T. M. Duman, "Capacity-approaching turbo coding and iterative decoding for relay channels," *IEEE Trans. Communications*, vol. 53, pp. 1895–1905, Nov. 2005.
- [8] U. Mitra and A. Sabharwal, "On achievable rates for complexity constrained relay channels," *Proc. 41st Allerton conf. on Communication, control and computing*, Oct. 2003.
- [9] A. Host-Madsen, "A new achievable rate for cooperative diversity based on generalized writing on dirty paper," *presented at ISIT'03*, 2003.
- [10] S. Yang and J. C. Belfiore, "Optimal space-time codes for the MIMO amplify and forward cooperative channel," *submitted to IEEE Trans. Info. Theory*, Sep. 2005.
- [11] A. Murugan, H. E. Gamal, M. O. Damen, and G. Caire, "A unified framework for tree search decoding: Rediscovering the sequential decoder," *to appear in the IEEE Trans. Info. Theory*, March 2006.

- [12] L. Zheng and D. N. C. Tse, "Diversity and multiplexing: A fundamental tradeoff in multiple antenna channels," *IEEE Trans. Info. Theory*, vol. 49, pp. 1073–1096, May 2003.
- [13] L. Zheng and D. N. C. Tse, "Diversity and multiplexing: A fundamental tradeoff in multiple antenna channels," *IEEE Trans. Info. Theory*, vol. 49, pp. 1073–1096, May 2003.
- [14] G. D. F. Jr., "Coset codes-part i: Introduction and geometrical classification," *IEEE Trans. Info. Theory*, vol. 34, pp. 1123–1151, Sept. 1988.
- [15] H.-A. Loeliger, "Averaging bounds for lattices and linear codes," *IEEE Trans. Inform. Theory*, vol. 43, pp. 1767–1773, Nov. 1997.
- [16] U. Erez and R. Zamir, "Lattice decoding can achieve $\frac{1}{2} \log(1 + \text{snr})$ on the awgn channel using nested codes," *IEEE Trans. Inform. Theory*, vol. 50, pp. 2293–2314, Oct. 2004.
- [17] E. Agrell, T. Eriksson, A. Vardy, and K. Zeger, "Closest point search in lattices," *IEEE Trans. Info. Theory*, vol. 48, pp. 2201–2214, Aug. 2002.
- [18] H. E. Gamal, G. Caire, and M. O. Damen, "Lattice coding and decoding achieve the optimal diversity-vs-multiplexing tradeoff of MIMO channels," *IEEE Trans. Inform. Theory*, June 2004.
- [19] B. Hassibi and B. Hochwald, "High rate codes that are linear in space and time," *IEEE Trans. Info. Theory*, vol. 48, pp. 1804–824, July 2002.
- [20] M. Katz and S. Shamai, "Transmitting to colocated users in wireless ad-hoc and sensory networks," *IEEE Trans. Inform. Theory*, vol. 51, pp. 3540–3563, Oct. 2005.
- [21] P. Mitran, H. Ochiai, and V. Tarokh, "Space time diversity enhancements using collaborative communications," *IEEE Trans. Inform. Theory*, vol. 51, pp. 2041–2057, June 2005.
- [22] A. Murugan, H. E. Gamal, M. O. Damen, and G. Caire, "A unified framework for tree search decoding: Rediscovering the sequential decoder," *to appear in the IEEE Trans. Info. Theory*, March 2006.




Figure 1: Performance of NAF relay with Golden constellation, with the CC outer code (denoted by GC+CC) and without any outer code(denoted by GC).




Figure 2: Pareto optimal diversity-multiplexing tradeoff for the DDF protocol with $N = 1, 2$ and ∞ .




Figure 3: Outage performance of DDF relay protocol with 3, 4, 5 and 6 segments.




Figure 4: Performance of DDF relay protocol (with 3 segments) vs. NAF relay protocol.




Figure 5: FER performance of CMA-NAF vs. Relay NAF protocol.




Figure 6: BER performance of CMA-NAF protocol with uncoded QAM vs. Relay NAF protocol with Golden constellation.




Figure 7: Performance and Complexity of MMSE-DFE Fano decoder with CMA NAF protocol, for $R = 2$ BPCU.





Figure 8: Performance and Complexity of MMSE-DFE Fano decoder with CMA NAF protocol, for $R = 4$ BPCU.